

Sense Driver White 3000lm 700mA Trailing edge dimming

Article code: 820080
EAN: 7021988200803



Electrical

System wattage: 26W
Voltage: 230V
Max. luminaires per circuit breaker: B10: 30, B16: 50, C10: 48, C16: 80

Light technic

Lifetime: 100,000

Control/Dimming

Type: Trailing edge dimming
Driver: 700mA

Protection

Luminaire class: Class II

Energy and approvals

Breeam: Fulfils Hea 01 for flicker free lighting

Materials and finish

Housing: Plastic
Colour: White

Mounting/Connection


Mounting: Recessed, Indoor
Plug: Includes cable and plug

Dimensions (mm)

Length (mm) L: 119
Width (mm) W: 53
Height (mm) H: 30
Weight (brutto/netto): 0.384 / 0.32

Packaging

Packing dimensions (mm): 400 x 45 x 100



	CU (Kv)	CU (Kv)	BA (°)	SENSE 3000lm DRIVER KIT PHASE DIM (700mA)	SENSE 4000lm DRIVER KIT NON DIM (1400mA)	SENSE 5000lm DRIVER KIT NON DIM (1400mA)	SENSE 3000lm DRIVER KIT DALI (1000mA)	SENSE 4000lm DRIVER KIT DALI (1400mA)	SENSE 5000lm DRIVER KIT DALI (1400mA)
SENSE OPAL 3-4000lm LED 3000K	80	3	110	2750lm/UCR-22 27W/128lm/W	4000lm/UCR-22 31.2W/127lm/W	+	2750lm/UCR-22 27W/128lm/W	4000lm/UCR-22 31.2W/127lm/W	+
SENSE OPAL 3-4000lm LED 4000K	80	3	110	2650lm/UCR-22 27W/126lm/W	3900lm/UCR-22 31.2W/126lm/W	+	2650lm/UCR-22 27W/126lm/W	3900lm/UCR-22 31.2W/126lm/W	+
SENSE OPAL 3000lm LED 3000K	80	3	110	2450lm/UCR-22 27W/121lm/W	3600lm/UCR-22 31.2W/121lm/W	+	2450lm/UCR-22 27W/121lm/W	3600lm/UCR-22 31.2W/121lm/W	+
SENSE OPAL 3000lm LED 4000K	80	3	110	2350lm/UCR-22 27W/121lm/W	3500lm/UCR-22 31.2W/121lm/W	+	2350lm/UCR-22 27W/121lm/W	3500lm/UCR-22 31.2W/121lm/W	+
SENSE PRISM 3-4000lm LED 3000K	80	3	90	2650lm/UCR-17 27W/126lm/W	3900lm/UCR-19 31.2W/126lm/W	+	2650lm/UCR-17 27W/126lm/W	3900lm/UCR-19 31.2W/126lm/W	+
SENSE PRISM 3-4000lm LED 4000K	80	3	90	2550lm/UCR-17 27W/123lm/W	3800lm/UCR-19 31.2W/123lm/W	+	2550lm/UCR-17 27W/123lm/W	3800lm/UCR-19 31.2W/123lm/W	+
SENSE PRISM 3000lm LED 3000K	80	3	90	2450lm/UCR-17 27W/121lm/W	3600lm/UCR-19 31.2W/121lm/W	+	2450lm/UCR-17 27W/121lm/W	3600lm/UCR-19 31.2W/121lm/W	+
SENSE PRISM 3000lm LED 4000K	80	3	90	2350lm/UCR-17 27W/118lm/W	3500lm/UCR-19 31.2W/118lm/W	+	2350lm/UCR-17 27W/118lm/W	3500lm/UCR-19 31.2W/118lm/W	+

Notes: Efficiency calculations are incl. driver.
Incl. driver: 7.14% loss depending on driver.

l



7 0 2 1 9 8 8 2 0 0 8 0 3